



Portable Radio RF-2400D

NOTE		•Specifications are subject to change without notice. Weight and dimensions are approximate.
TUNER	Frequency Range	FM 87 - 108MHz (50kHz step) AM 520 - 1730kHz (9/10kHz step)
	AFC (Automatic Frequency Control)	yes
	Tuning	Digital
	Tuning LED	yes (Red)
AUDIO SYSTEM	Power Output (RMS)	770mW (MAX)
SPEAKER SYSTEM	Speaker Size	10cm
TERMINAL	Earphone/ Headphone (3.5mm)	yes (mini/mono)
	Power Consumption (AC)	3W
OTHERS	Handle	yes
	Battery	DC 6V (R6/LR6, AA, UM-3) x 4
	Power Source AC	230 V, 50Hz
	DC In	-
Battery Life [Approx.]	Speaker	R6: FM 21 H, AM 20 H LR6: FM 52 H, AM 55 H
	Headphone	N/A, N/A
DIMENSIONS, WEIGHT	Dimensions (W x H x D) [Approx.]	234 x 122 x 82 mm
	Weight (without batteries) [Approx.]	690 g

Copyright © Panasonic Australia Pty Ltd