

## Portable AM/FM Pocket Radio RF-P50D

<b>NOTE</b>		•Specifications are subject to change without notice. Weight and dimensions are approximate.
<b>TUNER</b>	<b>Frequency Range</b>	FM 87 - 108MHz (50kHz step) AM 520 - 1730kHz (9/10kHz step)
	<b>Tuning</b>	Digital
	<b>Tuning LED</b>	yes (Red)
	<b>Power Output (RMS)</b>	150mW (MAX)
<b>AUDIO SYSTEM</b>		
<b>SPEAKER SYSTEM</b>	<b>Speaker Size</b>	5.7 cm
<b>TERMINAL</b>	<b>Earphone/ Headphone (3.5mm)</b>	yes (mini/mono)
	<b>Battery</b>	DC 3V (R6/LR6, AA, UM-3) x 2
<b>Power Source</b>	<b>AC</b>	-
<b>OTHERS</b>	<b>DC In</b>	-
	<b>Speaker</b>	R6: FM 24 H, AM 26 H, LR6: FM 64 H, AM 68 H
<b>Battery Life [Approx.]</b>	<b>Headphone</b>	R6: FM 38 H, AM 38 H, LR6: FM 94 H, AM 96 H
<b>DIMENSIONS, WEIGHT</b>	<b>Dimensions (W x H x D) [Approx.]</b>	69.5 x 117.4 x 29.7 mm
	<b>Weight (without batteries) [Approx.]</b>	111 g

Copyright © Panasonic Australia Pty Ltd